

Sony P2 Device Numbers

When a Controlled device responds correctly to the Device Type Request command (00.11) with the device type code the controlling device can setup the name and parameters correctly. There are 4,096 codes available, not all have been used although some have been used more than once.

One of the main features of the SR/MR remote controls/Synchronisers is the ability to auto-configure to suit the connected device. The device type code provides this information.

This list includes almost all of the devices that we know about, we try to keep it up to date. If you would like your product to be included in this list, or you find a device not in this list please E-Mail the product name and device type to us and we will include it for future reference. Our intention is to keep this list up to date, we can only do this with your help.

The parameter 'x' represents the timecode standard of the machine as follows:

0	SMPTE 29,97/30 frames per second
1	EBU 25 frames per second
2	Film 24 frames per second

CB Electronics also support a three byte ID where the third byte is defined as follows:

Bits 0..3 = Machine Number, allows multiple machines of the same type to be identified when connected to the system

Bits 4..7 = Number of tracks / 8

Example: Fx B2 21 = Pyramix 16 Tracks, Machine 1 (Displayed as PMX-16a)

0x.00	BVH-1100	0x.93	CB Timeline Lynx	1x.4C	VO-9850
0x.01	BVH-2000	0x.94	CB MRP-16	1x.80	BVU-900
0x.10	BVH-2000	0x.95	CB Ampex DCT700	1x.E0	Nagra-T
0x.11	BVH-2000	0x.96	CB Ampex VPR-3	1x.E1	Nagra-D
0x.14	BVH-2000P	0x.97	CB Ampex VPR-6	1x.F0	VO-5850
0x.15	BVH-2000P	0x.98	CB Ampex XVR-80	1x.FF	DMR-2000
0x.18	BVH-2180	0x.99	CB Ampex VPR-300		
0x.19	BVH-2180	0x.9A	CB Ampex VPR-80		
0x.1C	BVH-2180P/Stud V8	0x.A0	CB P2MMC	2x.00	BVW-10
0x.1D	BVH-2180P	0x.A1	CB TG-2	2x.01	BVW-40
0x.20	BVH-2500	0x.A2	CB PioneerDVD I/F	2x.02	BVW-11
	DVS-6/7/800C	0x.A3	CB P2DVD	2x.03	BVW-15
	/HDDF-500	0x.A4	CB P2MMC-USB	2x.10	BVW-35
0x.24	BVH-2500P	0xA5	CB Quicktime	2x.18	BVW-35P
0x.30	BVH-2700	0x.B0	CB SR-GEN	2x.20	BVW-60
0x.40	BVH-2800	0x.B1	CB SR-RDR	2x.21	BVW-65
0x.44	BVH-2800P	0x.E0	HDD-1000	2x.22	BVW-95
	DME-3/5/7000	0x.F0	HDV-1000	2x.23	BVW-96
0x.48	BVH-2830	0x.FF	DMR-2000	2x.24	BVW-70
0x.4C	BVH-2800P			2x.25	BVW-75 (GV-K2)
0x.50	BVH-3000	1x.00	BVU-800	2x.26	BVW-85P
0x.52	BVH-3000P	1x.01	BVU-820	2x.29	BVW-65P
0x.54	BVH-3000P	1x.02	BVU-850	2x.2A	BVW-95P
0x.60	BVH-3100	1x.03	BVU-870	2x.2C	BVW-70S
0x.62	BVH-3100P	1x.12	DAR OMR-8	2x.2D	BVW-75P
0x.64	BVH-3100P	12.12.2x.41	Datavideo DN-300	2x.2F	WBR-700
0x.70	CB Studer D820	1x.18	BVU-900	2x.30	BVW-50 (CVR-50)
0x.71	CB Studer TLS-1	1x.19	BVU-920	2x.40	PVW-2600
0x.72	CB Studer A807	1x.1C	BVU-950	2x.41	PVW-2800
0x.73	CB Studer A812		Radar-1	2x.42	PVW-2650
0x.74	CB Studer A820T	1x.20	SVO-5800	2x.45	BVW-D265
0x.75	CB Studer A820M	1x.21	SVP-5600	2x.46	BVW-D75
0x.81	CB Studer A820-24	1x.28	SVP-9020	2x.47	BVW-9000
0x.90	CB Dubber	1x.2C	SVO-9620	2x.50	UVW-1600
0x.91	CB AK ES1	1x.34	DAR-OMR8	2x.51	UVW-1800
0x.92	CB VS-1	1x.48	VO-9800	2x.52	UVW-1700G

2x.A0	SRW-5000	Ax.02	LVR-3/4000	D8.50	FF Digideck
2x.A1	SRW-5500	Ax.07	M2 AU-750	Dx.51	DADR-5032
2x.A2	SRW-5800	Ax.10	LVA-7/8000	Dx.52	DADR-5048
2x.E0	HDW-500	Ax.11	LVA-3/4000	Dx.53	DADR-5064
2x.E2	HDW-2000/M200P	Ax.20	CDP-3100	Dx.70	QuBit ST
2x.E3	HDW-2000	Ax.30	PCM-9000	Dx.71	QuBit EL/DS
2x.E4	HD CAM J-H3	Ax.40	BKDE-550 (TRUDI)	Dx.81	DPS-PVR
2x.F0	HDV-10	Ax.4D	Gallery VirtualVTR	Dx.90	DN-C680
2x.F9	HDV-500	Ax.50	Doremi V1	Dx.91	DN-M51050R
		Ax.80	SVHS AG-7750	Dx.A0	P2MMC-MX2424
3x.00	DVR-1000	Ax.81	SVHS AG-7650	Dx.A1	AVID Media Comp
3x.03	Augan-OMX-24	Ax.82	DS-850	Dx.A2	AVID A/S 16
3X.10	DVR-2000	Ax.86	AG-8700	Dx.A3	AVID A/S 32
3x.11	DVR-2100	Ax.88	DS555 SVHS	Dx.A8	AVID A/V 24
3x.E0	Bonsai	Ax.91	XDCAM Blue Ray	Dx.A9	AVID A/V 8
		Ax.A1	Soundmaster Atom	Dx.AA	AVID A/V 16
4x.00	DVR-10	Ax.C0	JoeCo BBR	Dx.AB	AVID A/V 32
4x.02	DVR-C10	Ax.F0	HDL-5800	Dx.E1	Protools 24T
4x.03	DVR-18			Dx.B0	Otari RADAR
4x.10	DVR-2	Bx.00	DVW-A500	Dx.C0	Genex GX2000
4x.20	DVR-20	Bx.01	DVW-A510	Dx.C1	Genex GX8000
4x.21	DVR-C10	Bx.02	DVW-CA500	Dx.C2	Genex GX8016
4x.22	DVR-28	Bx.03	DVW-CA510		OMX 24
4x.23	DVR-P20	Bx.10	DVW-500	Dx.C3	Genex GX8024
			DSr-85	Dx.C4	Genex GX8032
5x.00	APR-5003V	Bx.11	DVW-510	Dx.C5	Genex GX8040
5X.24	APR-24		DSR-80	Dx.C6	Genex GX8048
5x.33	AJD-750	Bx.12	DVW-C500		Genex GX8050
			DSR-60	Dx.C7	Genex GX8056
6x.02	PCM-3402	Bx.13	DVW-C510	Dx.C8	Genex GX8064
6X.03	PCM-3324S	Bx.30	DVW-250	Dx.D0	Dolby Drive
6X.05	PCM-3348 HRV	Bx.40	DNW-A100	Dx.D1	Dolby Drive
6X.07	PCM-3348 HR	Bx.41	DNW-A100	Dx.D4	dAVE SP
		Bx.45	DNW-A45/50	Dx.E1	Protools
7X.00	PCM-7030		DNW-A46	Dx.F3	Zeta 3
7X.01	PCM-7050	Bx.46	DNW-A75	Dx.F8	CB MC-1
7X.02	PCM-7010	Bx.48	DNW-A30	Dx.F9	LANC I/F
7X.03	PCM-800	Bx.49	DNW-30	Dx.FA	TimeMachine C-Lab
7X.04	PCM-7040	Bx.4A	DNW-220	Dx.FB	SyncStation
7x.A2	Alesis A1-2	Bx.4C	DNW-220		
7x.E0	M20	Bx.60	MSW-M2000	Ex10	RaveHD Spectsoft
7x.E1	M20-16	Bx.70	Sony J-3	Ex 20	XDubber
7x.E2	M20-24			Ex 30	OpenCube
7x.E3	M20-32	Dx.00	DME-5000	Fx.00	JVC CR-850
7x.E4	M20-40	Dx.01	V-MOD 100		Bosch BCN-50
7x.E5	M20-48		DME-9000	FE.01	Drastic VVTR
7x.E6	M20-56	Dx.02	DME-3000	Fx.02	Bosch BCN-52
7x.E7	M20-64	Dx.10	ScreenSound	Fx.03	Abekas A62/A66
		Dx.11	SL 9000j		Ampex VPR-3
8X.01	Yamaha DRU-8	Dx.12	Axiom		Diskus
8x.08	EVO-9800	Dx.13	APS	Fx.04	Abekas A64
8x.0C	EVO-9850	Dx.14	DMC/Scenaria		Ampex VPR-3
8x.10	DSR-85	Dx.15	Omnimix	Fx.05	Abekas A60
8x.11	DSR-80	Dx.16	VisionTrack		Ampex VPR-3
8x.12	DSR-60	Dx.17	Aysis Air	Fx.06	Ampex VPR-3
8x.14	DSR-2000	Dx.18	Avant		Abekas A53D
8x.15	DSR-1800	Dx.19	Axiom MT	Fx.07	Ampex VPR-6
		Dx.30	MAV-1000	Fx.08	Abekas A53D/A57
9x.00	DEM-1000	Dx.31	MAV-1200	Fx.09	Bosch DCR100
9x.10	HDDF-500	Dx.40	DME-9000	Fx.0A	JVC KR-M800
Ax.00	ASC-VR	Dx.50	DADR-5000	Fx.0B	JVC SA-F911
Ax.01	LVR-5/6000AP	Dx.50	ADSG 16		BRS-662

Fx.0C	Hit VL-D500	Fx.B2	Merging Pyramix
Fx.0D	Hit VL-D505	Fx.B3	Merging V.T.
Fx.0E	Hit VL-S100	Fx.B4	Merging VCube
Fx.0F	Fostex G-24		
	Fostex DVD-40	Fx C0	Chinkel Cappella
Fx.10	Fostex D-20		
Fx.10.30	Fostex D-30	Fx.D1	StarSync
Fx.10.10	Fostex D-10		
Fx.10.20	Fostex D-20	Fx.DE	Soundscape Sync Card
Fx.11	Abekas A84	Fx.DF	Synchronos Rythmo
Fx.12	Abekas A82	Fx E0	MOSAIC Rythmo
Fx.13	VPR 2/300		
Fx.14	VPR-305		
Fx.15	VDR-V100		
Fx.16	VDR-V100		
Fx.17	VDR-V100		
Fx.18	VDR-V100		
Fx.19	AJ-D350		
Fx.1A	MMR-8,MRP-16 MX2424		
Fx.1B	Tascam DA-60		
Fx.1C	Tascam DA-30		
Fx.1D	Tascam DA-88		
Fx.1E	Hit HD-1200		
Fx.1F	JVC BR-S822E		
Fx.20	Quickframe		
Fx.21	RTD-4224		
Fx.22	RCI 5/625		
Fx.23	RCI HD rt		
Fx.24	RCI HD nonrt		
Fx.25	DCT		
Fx.26	JVC BR-S800E DCT700		
Fx.27	Otari DTR-90		
Fx.28	Otari DTR-90		
Fx.29	MotionWorker		
Fx.2A	Studer D424		
Fx.31	Pioneer 9601		
Fx.32	JVC BR-S85E		
Fx.33	AG DVCPRO AJD750		
Fx.34	Akai DR8		
Fx.35	Akai DR16		
Fx.36	Akai DD1500		
Fx.37	DVS ProntoServer		
Fx.39	Akai DD8		
Fx.3C	ES/2		
Fx.3A	JVC BR-D92E DIGI- SVHS		
Fx.3D	AMS Encore		
Fx.43	360 Systems TCR-4		
Fx.44	360 Systems TCR-8		
Fx.51	Pioneer PRV-LX10 (DVD Recorder)		
Fx.88	Sondor		
Fx.90	CTM Kolibri		
Fx.A0	F'Light MFX3		
Fx.A1	F'Light Vivid		
Fx.A2	F'Light MFX-3A		
Fx.A3	F'Light V-Motion		
Fx.B0	Merging VCube		
Fx.B1	Merging Luxor 96		